**CT300**
Gang Charger
CTG2GC

1. Lift up the gang charger and plug the power supply into outlet on bottom.

2. Plug power supply into power outlet. Green LED under button illuminates.

3. Slide assembled frame with tablet into a slot on gang charger. **Note:** User interface LED indicates tablet position and charging status.

4. A flashing LED on the user interface indicates tablet is charging.

## Button Undocking:

5. When tablet is fully charged (solid LED on interface), push button. After an audible click, remove tablet.

## Changing to IR Key Undocking:

**(Read Steps 1-4 before beginning process)**

1. Disconnect power to charger (LED on user interface goes off).

2. Reconnect power. Within 90 seconds of turning the LED on, press the left interface button 5 times within 5 seconds

If 5 button presses take longer than 5 seconds, the operation will fail. **Return to "changing to IR key undocking".**

3 LED below the IR key window will flash. Bring IR key to window and push button on key within 10 seconds.

**Note: If LED stops flashing, the opportunity for IR Key operation has been missed. Return to "changing to IR key undocking".**

4 The LED below IR key window will stay on if change is successful.

5 Slide frame with tablet into a slot on gang charger. **Note: User interface LED indicates tablet position and charging status.**

6 A flashing LED on the user interface indicates tablet is charging.

## Undocking with IR Key:

7 Bring IR key to IR key window. Press button on IR Key. After an audible click, remove tablet from charger.

## Wall Mount Option:

8 If using wall mount option use measurements below to drill four #4 (M3) screws into wall. Hang Gang Charger on screws using the openings in the back of the unit.

**Note:** Use caution to make sure that the screws and wall properly account for 30lbs.

## Cable Lock Option:

9 A Kensington cable lock can be used in this area by way of the provided 3mm x 7mm slot.

## Tabletop Mount Option:

10 If using tabletop mounting option use measurements below. Two points are provided to be utilized for locking down onto flat horizontal surface. M5 x 0.8 machine screws can be used to secure the charger down.

SD0372 Rev0 07/18/16

**www.invue.com**

**NA / LATAM** // 704.752.6513 • 888.55.INVUE
**EMEA** // +31.23.8900150
**APAC** // +852.3127.6811

© 2016 InVue Security Products Inc. All rights reserved.
InVue is a registered trademark of InVue Security Products.